


CMB350A - PRELIMINARY 3480-3520 MHz Bandpass Filter

Features

- Low loss with high rejection and low ripple
- Superior power handling and reliability
- Part of the CMB family of Metro-cell TDD Bandpass Filters
- Choice for either PCB mounting with pins, or with various connectors (SMA, SMP-Max, etc.) and mounting brackets



Part Dimensions: 35 x 28 x 13 mm • 35g

Materials: Ag plated ceramic block

Applications

- Wireless Infrastructure applications
- High-performance carrier-grade TDD basestations up to 20W at the antenna port
- Wide-band DAS, Repeaters, or small-cells including support for WiFi co-location

Description

Ceramic waveguide bandpass filter based on ClearPlex technology supports TDD frequency bands. Provides superior rejection, insertion loss, reliability, as well as both peak and average power handling compared to other ceramic technologies. Performance is comparable to compact Air Cavity in dramatically smaller size.

Electrical Specifications

Parameter	Frequency (MHz)	Typical at 25°C	Spec. at 25°C	Spec. over -40°C to +85°C
Nominal Impedance	-	50 ohms	-	-
Average Input Power	-	-	-	32 Watt max
Peak Input Power	-	-	-	320 Watt max

Input-Output Response

Passband Insertion Loss (20 MHz avg)	3480 - 3520	1.5 dB		1.6 dB max
Passband Insertion Loss (single-point)	3480 - 3520	1.8 dB		2.2 dB max
Passband Ripple	3480 - 3520			<1.0 dB max
Passband Return Loss	3480 - 3520			16 dB min
Attenuation:	1 - 2700			>75 dB min
	2700 - 3440			>60 dB min
	3460			>25 dB min
	3600 - 3800			>55 dB min

NOTE: Use with RLF0380A lowpass filter to assure high-frequency suppression over 4.2-12.75GHz

Note: CTS tests each unit to the critical specifications above. Subsequent audits may deviate due to repeatability among different test systems which shall not exceed these allowances.

Specification Allowance	
Insertion Loss	0.1 dB
Return Loss	1.0 dB
Attenuation	1.0 dB



PRELIMINARY - CMB350A

3480-3520 MHz Bandpass Filter

Mechanical Drawing

PCB Layout

Packaging and Marking

